



PelcoNet™ NET300

IP NETWORK VIDEO TRANSMISSION

Product Features

- Send and Receive Live Video and Control Data Over Ethernet Networks
- Dual MPEG-4 Video Streams
- Full Integration with Pelco's Matrices, Genex® Multiplexers, Spectra® Domes, and Esprit® Positioning Systems
- Adjustable Bandwidth, Image Rate, and Quality
- View Video on PC, Analog Monitor, or Both
- NTSC and PAL
- Alarm Input and Relay Output
- Bidirectional Data Channel Via RS-232/422/485 Serial Port



The **NET300** can be used in three ways:

- **Standalone** – as a transmitter or receiver for a camera where BNC cable is not possible. This allows one-way video transmission for fixed cameras or the option of sending control signals to a Spectra® dome or Esprit® positioning system.
- **Analog to Ethernet "Bridge"** – as a way of using one or more **NET300s** connected to a system of Pelco matrices or Genex® multiplexers to view video from a vast number of camera analog inputs. In this application the analog device is being used as a "concentrator" to allow viewing of hundreds of cameras without incurring the cost of hundreds of encoders.
- **Complete Ethernet System** – as a way of controlling an unlimited number of cameras via **NET300s** by using Pelco's VMX series of matrix control software in a purely Ethernet or hybrid system. Ethernet systems involve using an encoder with each camera and using the Ethernet as a virtual matrix. This is cost efficient for new installations or add-ons to existing installations. Using the VMX300 as control software for existing systems as well as new Ethernet portions allows the user to build the industry's only truly "hybrid" CCTV system.

The **NET300** can display video on a PC using Internet Explorer®, an analog monitor, or both.

PelcoNet™ transmits (**NET300T**) or receives (**NET300R**) live video and data across existing Ethernet networks. Sending video over computer networks yields significant cost savings by using an existing computer network to monitor a remote site.

The **NET300** saves installation costs (no separate cabling required), allows toll-free operation (intranets), and saves management costs (single, uniform network).

With minimal setup, the **NET300** transmission system can be installed and running in minutes.

When using a **NET300T** and a **NET300R**, connect a camera to a transmitter and an analog monitor to a receiver. Then connect the transmitter and receiver to the network and configure IP addresses for the equipment using a standard terminal program or any Internet browser. If you need to control a camera (operate pan, tilt, and lens functions, or do presets and patterns), an RS-232/422/485 data interface links the keyboard controls to the network and then from the network to the camera system.

Instead of (or in addition to) a receiver and monitor, an Internet browser can be used at the receiving end to display video on a PC. On-screen keyboards in the **NET300** let you control the following devices over the network: System 9760®/9740™ or CM6700/CM6800 matrix controller, Genex multiplexers, Spectra domes, and Esprit positioning systems.

The **NET300T**, featuring dual MPEG-4 video streams, lets you use computer networks to interface your control and monitoring stations with remote camera sites, whether they are in the same building, across the country, or around the world.



DataFAX
SPEC: 22908
MANUAL: Not Available through DataFAX

C2908 / NEW 9-03



International Organization
for Standardization;
Registered ISO 9001



TECHNICAL SPECIFICATIONS

MODELS

| | |
|---------|---|
| NET300T | Network video transmitter that encodes video and control data for transmission over an IP network |
| NET300R | Network video receiver that decodes video and control data received from an IP network |

Minimum PC Requirements (as needed)

- PC (Pentium® 4 microprocessor, 1.6 GHz) with Windows®98/2000/XP or higher operating system
- 256 MB of RAM
- Gateway to the network
- 100 Mbit Ethernet card
- Sound card if using audio application
- Microsoft® Internet Explorer 6.0 (or higher), or free serial interface and terminal program, or PelcoNet NET300R (receiver) and video monitor
- DirectX® 8.1 or 9.0 application programming interface
- Screen resolution of 1024 x 768 or higher, 16- or 32-bit pixel color resolution
- Graphic Card: ATI RADEON™ 7500 or 8500, Matrox G 550 or Parhelia™, or NVIDIA® GeForce 3 or 4 with MPEG-4 playback capability

RELATED PRODUCTS

| | |
|----------|---|
| NET350 | IP network video system that transmits (NET350T) or receives (NET350R) live video, audio and control data across Ethernet networks. Features CompactFlash® and dual MPEG-4 video streams. |
| NET4001A | IP network video transmission system that transmits and receives live video, audio, and control data across Ethernet networks. Provides DVD quality video in MPEG-2 or MPEG-4 format. |
| VMX300 | Video management system that provides control and monitoring of both analog and digital video systems. Supports client-to-server, client-to-multiple servers, and server-to-server configurations. |
| NVR300 | Network video recorder that records video and audio over TCP/IP networks. Through its Ethernet interface, it can receive compressed data generated by the PelcoNet NET300, NET350, and NET4001A. The NVR300 indexes the data and then transfers it to an internal storage unit. Storage can be expanded externally. |

NETWORK PROTOCOL AND STANDARDS COMPATIBILITY

| | |
|------------------------|--|
| Internet Configuration | RTP, RTCP, UDP, TCP, IP, HTTP, SNMP, IGMP, ICMP, ARP, DHCP |
| Video Coding | MPEG-4 (M-JPEG in Server Push mode only) |
| Video Frame Rate | Up to 30 images/second |

INTERFACES

| | |
|-----------------------|--|
| Video Input or Output | 1, BNC, PAL/NTSC, 75 ohms, 1 Vp-p |
| LAN Interface | Ethernet 10/100BaseT autosensing, RJ-45 |
| LAN Data Rate | 9.6 Kbps to 1.5 Mbps |
| Data Interface | 1 RS-232/RS-422/RS-485, bidirectional (9-pin, D-sub) |
| Alarm Input | 2 terminal, 30 VDC maximum |
| Alarm Output | 1 terminal, 30 VDC, 1 A |

VIDEO

| | |
|------------------|--|
| Video Standard | PAL, NTSC |
| Video Image Size | 704 x 576 pixels (high resolution) 352 x 288 pixels (CIF) |

POWER

| | |
|-------------------|----------------------------------|
| Type | Plug power adapter |
| Operating Voltage | 12-24 VDC, power supply included |
| Power Consumption | Approximately 10 W |

ENVIRONMENTAL

| | |
|-----------------------|---|
| Operating Temperature | 32° to 122°F (0° to 50°C) |
| Operating Humidity | 80% maximum relative humidity, non-condensing |
| Storage Temperature | 4° to 140°F (-20° to 60°C) |
| Storage Humidity | 95% maximum relative humidity, non-condensing |

GENERAL

| | |
|-----------------|--|
| Dimensions | 3.4" W x 1.2" H x 4.5" D (8.6 x 3.1 x 11.4 cm) |
| Unit Weight | Approximately 0.4 lb (0.2 kg) without power supply |
| Shipping Weight | Approximately 2 lb (0.9 kg) |

CERTIFICATIONS

- CE, Class B
- cTUVus
- FCC, Class B

OPTIONAL ACCESSORIES

| | |
|----------|---|
| NET300RK | Rack mount for 1-5 units. Fits standard 19-inch EIA rack or console (1 RU). |
|----------|---|



Pelco Worldwide Headquarters:

3500 Pelco Way, Clovis, California 93612-5699 USA

USA & Canada Tel: (800) 289-9100 • FAX (800) 289-9150 • DataFAX (800) 289-9108

International Tel: (559) 292-1981 • FAX (559) 348-1120 • DataFAX (559) 292-0435

www.pelco.com

Spectra®, Espri®, Genex®, and System 9760® are registered trademarks of Pelco.

PelcoNet™ and System 9740™ are trademarks of Pelco.

Microsoft®, Windows®, Internet Explorer®, and DirectX® are

registered trademarks of Microsoft Corporation.

Pentium 4® is a registered trademark of Intel Corporation.

CompactFlash® is a registered trademark of SanDisk Corporation.

NVIDIA® is a registered trademark of NVIDIA Corporation.

ATI RADEON™ is a trademark of ATI Technologies Inc.

Parhelia™ is a trademark of Matrox Technologies Inc.

Specifications subject to change without notice.

©Copyright 2003, Pelco. All rights reserved.